



DO THE JOB RIGHT.

Firmware Update Guide

Description:

THC Firmware Update Guide

Item #:

66726

Issue Date (yy/mm/dd):

24/01/12

Issued By:

NC


Rev:

0


Page

1 of 3

- To update, download the “sfthc.bin” file to a USB drive with no other files on it. Do not modify the “sfthc.bin” file in any way.
- Start with the table powered on. Plug the USB drive into its port.
- Remove the Control Box cover panel by unfastening the screw at each corner.



- Unplug the power input connector at the top left of the motherboard.





DO THE JOB RIGHT.

Firmware Update Guide

Description:

THC Firmware Update Guide

Item #:

66726

Issue Date (yy/mm/dd):

24/01/12

Issued By:

NC


Rev:

0


Page

2 of 3

- Press F5 “Diagnose” then press F5 “T Update” and press enter to confirm updating. A blue screen will display.



- Plug the power input connector back into the top left of the motherboard. The update will begin automatically and display the progress percentage on the screen. It should last only a brief period.
- Once finished, the screen will display “Press Any Key” and you may press a key to continue.





DO THE JOB RIGHT.

Firmware Update Guide

Description:

THC Firmware Update Guide

Item #:

66726

Issue Date (yy/mm/dd):

24/01/12

Issued By:

NC

Rev:

0

Page

3 of 3

- Disconnect the USB drive and power cycle the table to reboot. Delete the update file from the USB drive.
- The table is ready for use again; you can confirm version 3.6 is shown in the bottom left of the THC settings menu.

